


| item number | for width of cable tray | for height of cable tray | Α | thickness of metal sheet | weight kg/ps | amount of bolts for connection | ٨ |
|------------------|-------------------------|-----------------------------------|-----|--------------------------------|-----------------|--------------------------------------|------------|
| NSO 90X50X62_S | 62 | 50 | 241 | 0,7 | 0,37 | 4 | ٨ |
| NSO 90X50X62_F | | | | | 0,44 | | |
| NSO 90X50X125_S | 125 | 50 | 241 | 0,7 | 0,48 | 4 | ٨ |
| NSO 90X50X125_F | | 30 | | | 0,57 | | 7/9 |
| NSO 90X50X250_S | 250 | 50 | 241 | 0,7 | 0,71 | 4 | ٨ |
| NSO 90X50X250_F | | | | | 0,91 | | |
| NSO 90X100X125_S | 125 | 100 | 291 | 0,7 | 0,79 | 8 | ٨ |
| NSO 90X100X125_F | 120 | 100 | 201 | 0,1 | 0,93 | | |
| NSO 90X100X250_S | 250 | 100 | 291 | 0,7 | 1,06 | 8 | ٨ |
| NSO 90X100X250_F | | | | | 1,35 | | |
| NSO 90X100X500_S | 500 | 100 | 291 | 0,7 | 1,62 | 8 | ٨ |
| NSO 90X100X500_F | | 100 | | | 2,10 | | (1) |





product description:

The rising elbow is designed for the transition between a horizontal and sloping (vertical) cable tray.

A bolt with a GMT surface finish is used for a tray with an F surface

finish.

These items can also be ordered in a varnished version.

surface finish:

S - Pre-Galvanized, zinc-layer 15 - 27 μm

F - Hot Dip Galvanized, zinc-layer 45 μ m (min. 35 μ m)

sales amount:

á 1 pc

certification:

EN 61537:02

classification ::

ČSN 73 0895 P 90-R DIN 4102-12 E 90 STN 92 0205 PS 90

Fire classification depends on the specific conditions of the cable tray, detailed in the catalog Systems with maintained functionality in fire

h products are approved for non-standard constructions

storage:

EN 60721-3-1





MARNING

Risk of injury from cutting

Although the cable trays are produced with maximum effort to minimize sharper edges, it is necessary to wear protective gloves to carry, grip and work with cable elements.

Electricity injury

As individual components of cable management systems are made of electrical conductive material, it is essential not to work with a system near live electrical parts. Infringement of the safety regulations may cause serious injury of health or death.

Safe Use

Under normal and foreseeable conditions of use, there are no risks to consumers, provided that proper installation and usage are carried out in accordance with the installation manual.

recycling codes:



1 25/02/2025